

ISL70024SEH, ISL73024SEH

200V, 7.5A Enhancement Mode GaN Power Transistor

FN8976
Rev. 3.00
Mar 8, 2018

The [ISL70024SEH](#) and [ISL73024SEH](#) are 200V N-channel enhancement mode GaN power transistors. These GaN FETs have been characterized for destructive Single Event Effects (SEE) and tested for Total Ionizing Dose (TID) radiation up to 100krad(Si) High Dose Rate (HDR) and 75krad(Si) low Dose Rate (LDR). Applications for these devices include commercial aerospace, medical, and nuclear power generation.

GaN's exceptionally high electron mobility and low temperature coefficient allows for very low $r_{DS(ON)}$, while its lateral device structure and majority carrier diode provide exceptionally low Q_G and near zero Q_{RR} . The end result is a device that can operate at a higher switching frequency with more efficiency while reducing the overall solution size.

By combining the exceptional performance of the GaN FET in a hermetically sealed Surface Mount Device (SMD) package with manufacturing in a MIL-PRF-38535 like flow results in best-in-class power transistors that are ideally suited for high reliability applications.

Applications

- Switching regulation
- Motor drives
- Relay drives
- Inrush protection
- Down hole drilling
- High reliability industrial



Figure 1. ISL70024SEH 4 Ld SMD Package

Features

- **Very low $r_{DS(ON)}$ 45m Ω (typical)**
- **Ultra low total gate charge 2.5nC (typical)**
- SEE tolerance ($V_{DS} = 160V, V_{GS} = 0V$)
 - Characterized at LET 86 MeV•cm²/mg
- Radiation hardness assurance testing (lot-by-lot)
 - High dose rate (50-300rad(Si)/s): 100krad(Si)
 - Low dose rate (0.01rad(Si)/s): 75krad(Si)
- Ultra small hermetically sealed 4 Ld Surface Mount Device (SMD) package
 - Package area: 42mm²
- Full military-temperature range operation
 - $T_A = -55^{\circ}C$ to $+125^{\circ}C$
 - $T_J = -55^{\circ}C$ to $+150^{\circ}C$

Related Literature

For a full list of related documents, visit our website

- [ISL70024SEH](#), [ISL73024SEH](#) product pages




Figure 2. On-State Resistance (+25°C)

1. Overview

1.1 Ordering Information

Ordering Part Number (Note 1)	Radiation Hardness (Total Ionizing Dose)	Temperature Range (°C)	Package (RoHS Compliant)	Package Drawing
ISL70024SEHML	HDR to 100krad(Si) LDR to 75krad(Si)	-55 to +125	4 Ld SMD	J4.A
ISL73024SEHML	LDR to 75krad(Si)	-55 to +125	4 Ld SMD	J4.A
ISL70024SEHMX	HDR to 100krad(Si) LDR to 75krad(Si)	-55 to +125	Die	-
ISL73024SEHMX	LDR to 75krad(Si)	-55 to +125	Die	-
ISL70024SEHX/SAMPLE (Note 2)	N/A	+25	Die	-
ISL73024SEHX/SAMPLE (Note 2)	N/A	+25	Die	-
ISL70024SEHL/PROTO (Note 2)	N/A	-55 to +125	4 Ld SMD	J4.A
ISL73024SEHL/PROTO (Note 2)	N/A	-55 to +125	4 Ld SMD	J4.A

Notes:


1. These Pb-free Hermetic packaged products employ 100% Au plate - e4 termination finish, which is RoHS compliant and compatible with both SnPb and Pb-free soldering operations.
2. The /PROTO and /SAMPLE parts are not rated or certified for Total Ionizing Dose (TID) or Single Event Effect (SEE) immunity. These parts are intended for engineering evaluation purposes only. The /PROTO and /SAMPLE parts meet the electrical limits and conditions across the temperature range specified in this datasheet and are of the same form and fit as the ISL70024SEHML/ISL73024SEHML devices. The /PROTO and /SAMPLE parts do not come with a Certificate of Conformance (C of C) and have no accompanying data or documentation.

Table 1. Key Differences Between Family of Parts

Part Number	Breakdown Voltage	Radiation Assurance
ISL70024SEH	200V	HDR to 100krad(Si) LDR to 75krad(Si)
ISL73024SEH	200V	LDR to 75krad(Si)
ISL70023SEH	100V	HDR to 100krad(Si) LDR to 75krad(Si)
ISL73023SEH	100V	LDR to 75krad(Si)

1.2 Pin Configuration

ISL70024SEH, ISL73024SEH
(4 Ld SMD)



Note: The ESD triangular mark indicates Pin #1. It is a part of the device marking and is placed on the lid in the quadrant where Pin #1 is located.

1.3 Pin Descriptions

Pin Number	Pin Name	Description
1	S	Source connection for the GaN FET.
2	SUB	Substrate connection for the GaN FET which is internally shorted in to source. Tie this pin to source on the PCB.
3	D	Drain connection for the GaN FET.
4	G	Gate connection for the GaN FET. Minimize trace inductance from driver to reduce over-stressing the gate.
NA	Lid	Internally tied to the source pin.

2. Specifications

2.1 Absolute Maximum Ratings

Parameter	Minimum	Maximum	Unit
V_{DS}	0	200	V
V_{DS} (Note 3)	0	160	V
V_{GS}	-4	6	V
ESD Rating (Drain-to-Source)		Value	Unit
Human Body Model (Tested per MIL-STD-883 TM3015)		2	kV
Machine Model (Tested per JESD22-A115C)		200	V
Charged Device Model (Tested per JS-002-2014)		750	V
ESD Rating (Gate-to-Source)		Value	Unit
Human Body Model (Tested per MIL-STD-883 TM3015)		500	V
Machine Model (Tested per JESD22-A115C)		200	V
Charged Device Model (Tested per JS-002-2014)		750	V

CAUTION: Do not operate at or near the maximum ratings listed for extended periods of time. Exposure to such conditions may adversely impact product reliability and result in failures not covered by warranty.

Note:

- Tested in a heavy ion environment at LET = 86.4 MeV·cm²/mg at +125°C (T_C).

2.2 Thermal Information

ISL70024SEH, ISL73024SEH in SMD Package J4.A			
Thermal Resistance	Typical	Maximum	Unit
θ_{JA} (Note 4)	42.0	-	°C/W
θ_{JC} (Note 5)	18.7	23.4	°C/W

Notes:

- θ_{JA} is measured in free air with the component mounted on a high-effective thermal conductivity test board with “direct attach” features. See [TB379](#).
- For θ_{JC} , the “case temp” location is on the solder terminations adjacent to the center of the package underside.

Parameter	Minimum	Maximum	Unit
Maximum Junction Temperature	-	+150	°C
Storage Temperature Range	-65	+150	°C

2.3 Recommended Operating Conditions

Parameter	Minimum	Maximum	Unit
Temperature	-55	+125	°C
V_{DS}	0	160	V
I_D ($V_{GS} = 5.0V$, $T_C = +25^\circ C$) (Note 6)	0	7.5	A
I_D ($V_{GS} = 5.0V$, $T_C = +105^\circ C$) (Note 6)	0	4.5	A

Note:

- $T_J = +150^\circ C$. Current limited by package constraints.

2.4 Electrical Specifications

Unless otherwise noted, $V_{DS} = 160V$. **Boldface limits apply across the operating temperature range, $-55^{\circ}C$ to $+125^{\circ}C$; over a total ionizing dose of 100krad(Si) with exposure at a high dose rate of 50-300rad(Si)/s; or over a total ionizing dose of 75krad(Si) with exposure at a low dose rate of <10mrads(Si)/s.**

Parameter	Symbol	Test Conditions	Min (Note 8)	Typ (Note 7)	Max (Note 8)	Unit
Static Characteristics						
Drain-to-Source Breakdown Voltage	BV_{DSS}	$V_{GS} = 0V, I_D = 125\mu A$	200	-	-	V
Drain-to-Source Leakage Current	I_{DSS}	$V_{DS} = 160V, V_{GS} = 0V$	-	1	115	μA
Drain-to-Gate Leakage Current	I_{GSX}	$V_{DS} = 160V, V_{GS} = 0V$	-	1	115	μA
Gate-to-Source Forward Leakage	I_{GSS}	$V_{GS} = 5V$	-	0.8	2.5	mA
Gate-to-Source Reverse Leakage		$V_{GS} = -4V$	-100	-20	-	μA
Gate Threshold Voltage	$V_{GS(th)}$	$V_{DS} = V_{GS}, I_D = 1.5mA$	0.8	1.4	2.5	V
Drain-to-Source ON-Resistance	$r_{DS(ON)}$	$V_{GS} = 5V, I_D = 7A$	-	45	110	m Ω
Source-to-Drain Forward Voltage	V_{SD}	$I_S = 0.5A, V_{GS} = 0V$	0.8	1.8	3.5	V
Dynamic Characteristics						
Input Capacitance	C_{ISS}	$V_{DS} = 100V, V_{GS} = 0V$ (Note 9)	-	270	-	pF
Output Capacitance	C_{OSS}	$V_{DS} = 100V, V_{GS} = 0V, T_A = +25^{\circ}C$	-	150	200	pF
Reverse Transfer Capacitance	C_{RSS}	$V_{DS} = 100V, V_{GS} = 0V$ (Note 9)	-	1	-	pF
Gate Resistance	r_G	$T_A = +25^{\circ}C$ (Note 9)	-	60	-	m Ω
Total Gate Charge	Q_G	$V_{DS} = 100V, V_{GS} = 5V, I_D = 7A, T_A = +25^{\circ}C$	-	2.5	5	nC
Gate Charge at Threshold	$Q_{G(th)}$	$V_{DS} = 100V, I_D = 7A$ (Note 9)	-	0.4	-	nC
Gate-to-Source Charge	Q_{GS}	$V_{DS} = 100V, I_D = 7A, T_A = +25^{\circ}C$	-	0.8	2.0	nC
Gate-to-Drain Charge	Q_{GD}	$V_{DS} = 100V, I_D = 7A, T_A = +25^{\circ}C$	-	0.6	2.0	nC
Output Charge	Q_{OSS}	$V_{DS} = 100V, V_{GS} = 0V$ (Note 9)	-	23	-	nC

Notes:

7. Typical values shown are not guaranteed.
8. Parameters with MIN and/or MAX limits are 100% tested at $-55^{\circ}C$, $+25^{\circ}C$, and $+125^{\circ}C$, unless otherwise specified.
9. Limits are established by characterization and/or design and are not tested.

3. Typical Performance Curves

Unless otherwise noted, $V_{DS} = 160V$; $T_A = +25^\circ C$.




Figure 3. Output Characteristics (+25°C)




Figure 4. Output Characteristics (+125°C)




Figure 5. Output Characteristics (-55°C)




Figure 6. Transfer Characteristics




Figure 7. On-State Resistance (+25°C)




Figure 8. On-State Resistance (+125°C)

Unless otherwise noted, $V_{DS} = 160V$; $T_A = +25^\circ C$. (Continued)




Figure 9. On-State Resistance (-55°C)




Figure 10. Capacitance (Linear Scale)




Figure 11. Capacitance (Log Scale)




Figure 12. Reverse Drain-Source Characteristics




Figure 13. Normalized On-State Resistance




Figure 14. Normalized Threshold Voltage

Unless otherwise noted, $V_{DS} = 160V$; $T_A = +25^\circ C$. (Continued)




Figure 15. Safe Operating Area




Figure 16. Safe Operating Area (Derated)


4. Die Characteristics

Table 2. Die and Assembly Related Information


Die Information	
Dimensions	2766 μ m x 950 μ m (108.90 mils x 37.40 mils) Thickness: 685 μ m (26.97 mils)

ISL70024SEH, ISL73024SEH

Solder Bar View



Side View



Color Key:

- Pads in Green are the Source
- Pads in Orange are the Drain
- Pad in Blue is the Gate
- Pad in Purple is the Substrate

Table 3. Dimensions

Dimension	Min (μ m)	Nominal (μ m)	Max (μ m)
A	2736	2766	2796
B	920	950	980
c	697	700	703
d	247	250	253
e	168	183	198
f	245	250	255
g	600	600	600
h	450	450	450
i	235	250	265




5. Revision History

Rev.	Date	Description
3.00	Mar 8, 2018	Updated ordering information table by correcting /SAMPLE part numbers and adding Die where applicable. Updated Section 4 heading from "Die and Assembly Characteristics" to "Die Characteristics".
2.00	Feb 5, 2018	Changed 55mΩ to 45mΩ in the first Features bullet.
1.00	Jan 15, 2018	Updated Figure 1. Added ISL73024SEH part to datasheet. Ordering Information table on page 2 and updated Note 2. Added Table of Differences on page 2. Electrical Spec table - updated Note 9 on page 5. Added Die and Assembly Characteristics section on page 9. Removed "About Intersil" section. Updated disclaimer and moved to last page.
0.00	Oct 4, 2017	Initial release

6. Package Outline Drawing


For the most recent package outline drawing, see [J4.A](#).

J4.A
 4 PIN 9.0mmx4.7mm HERMETIC SURFACE MOUNT PACKAGE
 Rev 0, 2/16



NOTES:

1. The corner shape (radius, chamfer, etc.) may vary at the manufacturer's option from that shown on the drawing.
2. The package thickness dimension is the package height before being solder dipped.
3. Dimensions are in millimeters.



TYPICAL RECOMMENDED LAND PATTERN

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.
Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
6. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
7. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
8. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
9. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
10. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
11. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.
(Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.
(Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.4.0-1 November 2017)



SALES OFFICES

Renesas Electronics Corporation

<http://www.renesas.com>

Refer to "<http://www.renesas.com/>" for the latest and detailed information.

Renesas Electronics America Inc.

1001 Murphy Ranch Road, Milpitas, CA 95035, U.S.A.
Tel: +1-408-432-8888, Fax: +1-408-434-5351

Renesas Electronics Canada Limited

9251 Yonge Street, Suite 8309 Richmond Hill, Ontario Canada L4C 9T3
Tel: +1-905-237-2004

Renesas Electronics Europe Limited

Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K
Tel: +44-1628-651-700, Fax: +44-1628-651-804

Renesas Electronics Europe GmbH

Arcadiastrasse 10, 40472 Düsseldorf, Germany
Tel: +49-211-6503-0, Fax: +49-211-6503-1327

Renesas Electronics (China) Co., Ltd.

Room 1709 Quantum Plaza, No.27 ZhichunLu, Haidian District, Beijing, 100191 P. R. China
Tel: +86-10-8235-1155, Fax: +86-10-8235-7679

Renesas Electronics (Shanghai) Co., Ltd.

Unit 301, Tower A, Central Towers, 555 Langao Road, Putuo District, Shanghai, 200333 P. R. China
Tel: +86-21-2226-0888, Fax: +86-21-2226-0999

Renesas Electronics Hong Kong Limited

Unit 1601-1611, 16/F., Tower 2, Grand Century Place, 193 Prince Edward Road West, Mongkok, Kowloon, Hong Kong
Tel: +852-2265-6688, Fax: +852 2886-9022

Renesas Electronics Taiwan Co., Ltd.

13F, No. 363, Fu Shing North Road, Taipei 10543, Taiwan
Tel: +886-2-8175-9600, Fax: +886 2-8175-9670

Renesas Electronics Singapore Pte. Ltd.

80 Bendemeer Road, Unit #06-02 Hyflux Innovation Centre, Singapore 339949
Tel: +65-6213-0200, Fax: +65-6213-0300

Renesas Electronics Malaysia Sdn.Bhd.

Unit 1207, Block B, Menara Amcorp, Amcorp Trade Centre, No. 18, Jln Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia
Tel: +60-3-7955-9390, Fax: +60-3-7955-9510

Renesas Electronics India Pvt. Ltd.

No.777C, 100 Feet Road, HAL 2nd Stage, Indiranagar, Bangalore 560 038, India
Tel: +91-80-67208700, Fax: +91-80-67208777

Renesas Electronics Korea Co., Ltd.

17F, KAMCO Yangjae Tower, 262, Gangnam-daero, Gangnam-gu, Seoul, 06265 Korea
Tel: +82-2-558-3737, Fax: +82-2-558-5338